

# MAGEWELL

## Pro Capture HDMI 4K Plus LT Technical Specifications

PRELIMINARY, SUBJECT TO CHANGE WITHOUT NOTICE

Copyright (c) 2011–2023 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. Windows, DirectShow and DirectSound are trademarks or registered trademarks of Microsoft Corporation. OS X and macOS are trademarks or registered trademarks of Apple Inc.

Revised on 01/12/2023

### Supported OS

- Windows
  - Windows 7/8/8.1/10/11/Server 2008/Server 2008 R2/Server 2012/Server 2016 (x86 & x64) and above
- Linux (support x86, x64 & ARM architecture)
  - Ubuntu 12.04/14.04/16.04/17.04/17.10/18.04 (x86 & x64) and above
  - CentOS 6.5/7 (x86 & x64) and above
  - Fedora 25/26/27 (x86 & x64) and above
  - Red hat 6.5 (x86 & x64) and above
  - Other Linux OS with kernel version 2.6.35 and above
- Mac
  - OS X 10.9/10.10/10.11 and above
  - macOS\* 10.12/10.13/10.14/10.15/11/12/13 (It does not support macOS 14 yet.)

\* More on the way with the upcoming support for macOS 14.x.

### Recommended OS (tested)

- Windows
  - Windows 7 Ultimate/8.1 Enterprise/10 Enterprise/Server 2008 R2 DataCenter/Server 2012 R2 DataCenter/Server 2016 R2 DataCenter (x86 & x64)
- Linux
  - Ubuntu 12.04/14.04/16.04 (x86 & x64)
  - Ubuntu 17.04/17.10/18.04 (x64)
  - CentOS 6.5/7.2 (x86 & x64)
  - Fedora 25/26 (x64)
  - Red hat 6.5 (x86 & x64)
- Mac
  - OS X 10.9.5/10.10/10.11.2/10.11.3/10.11.4
  - macOS 10.12/10.13.2/10.13.3/10.14.3/10.15/11/12/13

### Supported APIs

- Windows
  - DirectShow
  - DirectKS
  - Wave API/DirectSound/WASAPI
- Linux
  - V4L2
  - ALSA
- macOS
  - AVCaptureSession
  - AudioUnit

### Supported Software

- VLC

- VirtualDub
- OBS
- XSplit
- vMix
- VidBlaster
- Wirecast
- Microsoft Media Encoder
- Adobe Flash Media Encoder
- Any other DirectShow/V4L2/AVCaptureSession encoding/streaming software

## Input Interfaces

- HDMI
  - DVI-D 1.0
  - HDMI 2.0

## Host Interface

- PCIe Gen2 x4

## Loop-through Interface

- HDMI
  - DVI-D 1.0
  - HDMI 2.0

## Input Features

- Support for input video resolutions up to 4096x2160 pixels

## HDMI Specific Features

- 594MHz HDMI receiver
- Adaptive HDMI equalizer
- Support for customized EDID
- Support for extraction of AVI/Audio/SPD/MS/VS/ACP/ISRC1/ISRC2/Gamut/HDR/VBI InfoFrames
- Full colorimetry support
- Support for 8/10/12-bit color depths
- Support for RGB 4:4:4, YCbCr 4:4:4, YCbCr 4:2:2 color sampling
- Support for up to 8-channel IEC60958/IEC61937 audio streams via SDK
- Support for extraction of audio formation information & channel status data
- Support for extraction of video timing information
- Support for extraction of 3D format information
- Support for extraction of Sony/Canon DSLR time code
- Support for Side-by-Side Half, Top-and-Bottom, Frame Packing 3D mode.
- Support for HDR10

## Video Capture Formats

- Support for capture image resolutions up to 4096x2160 pixels
- Support for capture frame rates up to 144fps (Actual capture frame rate can be limited by PCIe bandwidth & image resolution)
- Support for 4:2:0 8-bit capture formats: NV12, I420, YV12
- Support for 4:2:2 8-bit capture formats: YUY2, YUYV, UYVY
- Support for 4:4:4 8-bit capture formats: V308, IYU2, V408, BGR24, BGR32
- Support for 4:4:4 10-bit capture formats: V410, Y410
- More capture formats are supported via Magewell Capture SDK

## Video Processing Features

- Two video processing pipelines with ~720Mpixels/s processing bandwidth for each one
- Full 10-bit video processing
- Video cropping
- Video scaling
- Video de-interlacing

- Weave
- Blend top & bottom field
- Top field only
- Bottom field only
- Video aspect ratio conversion
  - Auto or manual selection of input aspect ratio
  - Auto or manual selection of capture aspect ratio
  - Three aspect ratio conversion modes: Ignore (Anamorphic), Cropping or Padding (Letterbox or Pillarbox)
- Video color format conversion
  - Auto or manual selection of input color format & quantization range
  - Auto or manual selection of capture color format, quantization range & saturation range
  - Support for RGB, YCbCr 601, YCbCr 709, YCbCr 2020 color formats
  - Support for Limited or Full quantization range
  - Support for Limited, Full & 'Extended gamut' saturation range
- Video frame rate conversion
- Video OSD composition
  - Support for PNG OSD image (up to 4096x2160)
  - Support for dynamic loading of RGBA OSD image via SDK

## Multiple Cards per System

- Support for multiple cards plugged to one system
- On-board rotary switch to set card number, with 16 positions from 0 to F
- System hardware device tree will display "01: Pro Capture HDMI 4K+ LT" when rotary switch is set to 1, and so on
- The video and audio device names displayed in your software will include the card number (set by the rotary switch)

## Multiple Capture Streams

- Unlimited capture streams for any one input channel
- Independent cropping, aspect ratio, color format, resolution, frame rate, de-interlacing and color adjustment settings for each individual stream

## Ultra Low Latency Support

- Latency of 64 video lines
- Partial notification mode in SDK

## Timestamp & A/V Synchronization

- Hardware based 100ns high resolution clock
- Audio frames (192 audio samples) & video frames are stamped with hardware clock
- Hardware clock can be synchronized across cards (via SDK)

## Video Capture SG-DMA

- ~1600MB/s per channel DMA bandwidth in PCIe 2.x system
- ~800MB/s per channel DMA bandwidth in PCIe 1.x system
- Support for auto detection of Intel tiled GPU surface
- Support for DirectGMA for AMD video adapter chipsets
- Support for GPUDirect for Nvidia video adapter chipsets

## SDK

- Magewell Capture SDK for easy integration, maximum flexibility and performance

## Windows Driver Tweaks

- All options can be controlled by three levels of registry key: global level, product level and device level
- Video, Audio, Crossbar filter names can be customized via registry keys

## Firmware Upgrade

- Multiple cards in one system can be upgraded simultaneously
- Cards can be upgraded without a system power shutdown (In most cases, even a reboot is not needed)
- Safe upgrade. If power off or system break down occur when the firmware is being upgraded, it will automatically

restore to the initial version.

## LED Indicator

- Status LEDs indicate the working state of each channel:
  - Pulsing slowly: input signal unlocked
  - On: input signal locked
  - Double blinks: memory failed or FPGA configuration failed
  - Off: firmware or power supply abnormal

## Form Factor

- Low profile PCIe x4 Add-on Card
- 140mm x 68.88mm (without PCI bracket)

## Power Consumption

- Max current at 12V: ~ 0.48 A
- Max current at 3.3V: ~ 0.82 A
- Max power consumption: ~ 8.08 W

## Working Environment

- Operating temperature: 0 to 60 deg C
- Storage temperature: -20 to 70 deg C
- Relative Humidity: 5% to 90% non-condensing