



kramer

AAD-OUT2-F16

2-Channel Analog & Digital Audio Output Card



AAD-OUT2-F16 is a two-channel analog and digital output card for the VS-1616 Series Modular Multi-Format Digital Matrix Switchers. The AAD-OUT2-F16 outputs two analog and digital signals from the chassis

FEATURES

- Balanced Analog Audio over Terminal Block Connector
- S/PDIF Digital Audio over RCA Connector



kramer

TECHNICAL SPECIFICATIONS

PORTS:	2 S/PDIF (digital audio) on RCA connectors, 2 balanced audio stereo (analog audio) on 5-pin terminal blocks
TOTAL BANDWIDTH:	Analog (-3db): >100kHz, Digital: 32kHz - 192kHz sample frequency
POWER CONSUMPTION:	5.8W
OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-40° to +70°C (-40° to 158°F)
HUMIDITY:	10% to 90%, RHL non-condensing
SAFETY REGULATORY COMPLIANCE:	CE
ENVIRONMENTAL REGULATORY COMPLIANCE:	Complies with appropriate requirements of RoHs and WEEE
Product Dimensions	19.00cm x 13.00cm x 2.00cm (7.48" x 5.12" x 0.79") W, D, H
Product Weight	0.2kg (0.4lbs) approx
Shipping Dimensions	34.50cm x 16.50cm x 5.20cm (13.58" x 6.50" x 2.05") W, D, H
Shipping Weight	0.3kg (0.6lbs) approx