

## BT8577

### BOLT-DOWN POLE MOUNTED DIGITAL SIGNAGE STAND WITH RETRACTABLE BASE

BT8577 is a stylish display stand designed for use with screens up to 75". The retractable floor base allows the stand to be smoothly moved up to 400mm backwards; ideal for servicing and maintenance of hardware. Suitable for screens with VESA fixings up to 600x400, the screen can be easily mounted at any height on the 1.8m pole. Accessories such as shelves can also be added using a Ø50mm collar.

#### SPECIFICATIONS


Recommended screen size	up to <b>75"</b>
Max load	<b>50kg</b>
VESA® & non-VESA fixings	<b>600mm x 400mm</b>
Pole diameter	<b>Ø50mm pole</b>
Pole length	<b>1.6m</b>
Base dimensions	W: <b>262mm</b> H: <b>88mm</b> D: <b>426-832mm</b>
Maximum retraction	<b>400mm</b>
Colour	<b>Black</b>

#### FEATURES

- 1 Ideal for shop fronts, close-to-the-window installations
  - 2 Sliding floor base retracts the pole/display stand backwards
  - 3 Collar compatible accessories can be fitted directly to the pole
  - 4 Suitable for landscape or portrait mounting
- Small footprint for an unobtrusive installation into confined areas
  - Internal storage area in base, ideal for power supplies, extension cord etc.
  - Lockable mechanism
  - Integrated cable management
  - All mounting hardware included



RECOMMENDED MAX SCREEN	MAX LOAD	MAX VESA	POST INSTALL ALIGNMENT	COLLAR COMPATIBLE	QR CODE
75" 190cm	50kg	600 x 400	← →	⊙	



© 2024 B-Tech AV Mounts Components Ltd. All rights reserved.  
The BT logo and B-Tech logo are registered trademarks of B-Tech AV Mounts Co. Ltd.  
We reserve the right to change the technical or physical specifications without prior notice. The B-Tech logo and B-Tech AV Mounts Co. Ltd. are registered trademarks of B-Tech AV Mounts Co. Ltd.  
B-Tech AV Mounts Co. Ltd. is not responsible for any damage caused by improper installation, use, or misuse of the product. B-Tech AV Mounts Co. Ltd. is not responsible for any damage caused by fire or theft.  
Specification does not constitute an offer. All specifications are subject to change without prior written permission. B-Tech AV Mounts Co. Ltd. is not responsible for any damage caused by fire or theft.

SS-BT8577-290224